



Pure IP™ Reader Controller Accessories



Reader covers

Overview

Schlage® offers a variety of accessories and replacement parts to ensure your reader controllers are always secure and performing well.

Reader Controller Covers

Replacement reader covers can be used to replace faded or cracked covers.

Advanced Security Module

Add an additional level of security for exterior doors, the advanced security module kit prevents the lock wires from being in contact with the unsecure side of the door.

Quick-Connect Cable

The quick connect cable allows the installer to connect the necessary reader controller wires without the hassle of the reader controller hanging off the other end. Simply connect the wiring harness and plug the reader controller in, it's that easy.

Magnetic Lock Kit

This part protects your reader controller from in-rush voltages and is primarily used for magnetic door locks.

Enrollment Reader Stand

Make the enrollment process even easier and quicker with this enrollment reader stand.

Color Options



Black
(standard)



Advanced Security Module



Quick-connect cable



Magnetic lock kit



Enrollment reader stand

Specifications



Part	Cover	Cover	Cover
Part number C1	47317541	47317539	47317540
Part number C2	47787013-SCH	47787014-SCH	47787015-SCH
Corresponding controller reader model	RC11	RC15	RCK15
Reader controller type	Mullion	Single gang	Single gang with keypad
Dimensions (HxWxD)	5.91" x 1.72" x 0.81"	5.1" x 3.25" x 0.76"	5.1" x 3.25" x 0.76"
Material	PNT polymer	PNT polymer	PNT polymer



Part	Quick Connect Cable/Pigtail	Advanced Security Module (ASM)	Magnetic Lock Kit - In Rush Suppressor	RC15 Enrollment Reader Stand
Part number	47274561 - 10 FT Cable 47274562 - 25 FT Cable 47609539 - RC04 to RC11/ RC15 Adapter Cable 47884474- 18" Pigtail Cable	ACC-EDK-3A	ACC-IRS-4700	47962621
Product specifications	<ul style="list-style-type: none"> 12 pin snap-in MOLEX connector Jacketed cable for protection and improved cable pulls 12 conductor cable, 22 AWG wires Cable jacket pre-stripped for connections to the door's components Being detachable simplifies the system's maintenance and troubleshooting 	<ul style="list-style-type: none"> For exterior doors, this kit provides an increased level of security by preventing the lock wires from being in contact with the unsecure side of the door Durable plastic enclosure Polycarbonate blend, UV stabilized Potted for greater weather resistance Powered by Schlage reader-controller; no additional power required Rated for 3 amps at 12v DC Proprietary encrypted serial data 2 sets of terminal blocks for easy installation Two LED indicators Required for magnetic lock installations powered via PoE Dimensions: 2-3/4" X 1-1/4" X 3/4" 	<ul style="list-style-type: none"> Any installation that is using magnetic locks that are equipped with a "quick-release feature" should have this in-rush protection installed Dimensions: 1-1/4" x 1-1/4" x 2-1/4" 	<ul style="list-style-type: none"> Desktop stand designed to hold RC15 reader when used as an enrollment reader for Zentra or other PACS partners RC15 reader fits tight and back slot allows for IP Pigtail to sit Correctly positions credential fobs for easy enrollment into software Works with both the C1 and C2 cover designs Dimensions: 4" x 3-1/2" x 5" 1/4"

Allegion, the Allegion logo, Schlage and the Schlage logo are trademarks of Allegion plc, its subsidiaries and/or affiliates in the United States and other countries. All other trademarks are the property of their respective owners.